

## HR-2003 ZigBee Module User Manual

### Function

#### RF/layout

- -Adapt to the 2.4-GHz IEEE 802.15.4 RF transceiver
- -High receiver sensitivity and robustness
- -Programmable output power up to 21 dBm
- -Only power Can communicate
- -16-mm × 28-mm Stamps package
- -Suitable for system configuration in line with the worldwide radio frequency

Rate regulations: ETSI EN 300 328 and EN 300440 (Europe), FCC CFR47 Part 15 (U.S.)

And ARIB STD-T-66 (Japan)

#### • Low power consumption

- -Active Mode RX (CPU Idle): 27 mA
- -Active Mode TX 20dBm (CPU Idle): 166mA
- -Power mode 1 (4 μs wake-up): 0.2 mA
- -Power mode 2(Sleep timer running): 1 μA
- –Power mode 3 (external interrupt):  $0.4~\mu A$
- -Wide supply voltage range (2 V-3.6 V)

#### Microcontrollers

- -Excellent performance and low power code prefetch function consumption of 8051 microcontroller core
- -32,64 -,128,256-KB system programmable flash
- -8-KB RAM, has number holding capacity under variety of power supply
- -Support for hardware debugging

#### · Default firmware

-Provide transparent serial, frame format , Various operating parameters can be configured using the configuration tool, the user can apply do not program

#### · Peripherals

- -Powerful 5-channel DMA
- -IEEE 802.5.4 MAC timer, general-purpose timer

(A 16-bit timer, an 8-bit timer)

- -IR generation circuit
- -32-kHz sleep timer with capture functionality
- -Hardware support CSMA/CA
- -Support accurate digitization RSSI/LQI
- -Battery monitor and temperature sensor
- -7 inputs and configurable resolution 12-bit ADC
- -AES Security coprocessor
- 2 Powerful USART supports a variety of serial communications protocol
- -18 general I / O pins (17 × 4 mA, 20 mA)
- -Watchdog Timer

#### Development Tool

- -CC2530 development kit
- -CC2530ZigBee®development kit
- -For the RF4CE CC2530 RemoTI ™ Development Kit
- -SmartRF™ software
- -Packet sniffer
- -Available IAR Embedded Workbench

#### Application

- 2.4-GHz IEEE 802.15.4 system
- RF4CE Remote control systems (greater than 64-KB Flash)
- · ZigBee system (256-KB flash)
- · Home / building automation
- · lighting system
  - · Industrial control and monitoring
  - Low-power wireless sensor networks
  - · Consumer electronics
  - Healthcare

RemoTI、SmartRF 、 Z-Stack Is trademark of Texas Instruments。

IAR Embedded Workbench is trademark IAR Systems.

Approvals

ZigBee Is a registered trademark ZigBee Alliance. All other trademarks are property their owners.

Remarks : The follow records of TT2530  $\,$  and TT2530  $\,$  is based on the T=25°C and VDD = 3 V, unless other explanations

Performance	TT2530	TT2530		
Use Chip	CC2530	CC2530+CC2591		
Interface	SMT	SMT		
Serial Interface Options	3V TTL	3V TTL		
Serial Data Rate	Up to 115.2 Kbps	Up to 115.2 Kbps		
RF Baud Rate	250 Kbps	250 Kbps		
Receive Current (Typical) (Active Mode RX, CPU idle)	24 mA	27 mA		
Transmit Current (Typical) (Active Mode TX at 1 dBm, CPU idle)	29mA	166 mA		
Channels	16	16		
Security	128 bit AES & SSP	128 bit AES & SSP		
Radio Frequency	TT2530	TT2530		
Frequency Band (software-selectable)	2400-2483.5 MHz	2400-2483.5 MHz		
Modulation	DSSS QPSK	DSSS QPSK		
Output Power	-28 dBm 4.5 dBm variable	-10 dBm 22.5 dBm variable		
Voltage	2. OV - 3. 6V	2. OV - 3. 6V		
Sensitivity (Typical) (@ full RF data rate)	-97 dBm typical	-98.8 dBm (High Gain Mode) -90.4 dBm (Low Gain Mode)		
Range (typical, depends on antenna/environment)	Up to 150 m	800~1600m		
Environmental	TT2530	TT2530		
Temperature	-40°C +125°C	-40°C +85°C		
Physical	TT2530	TT2530		
Dimensions	(16 x 28 x 3 mm)	(16 x 28 x 3 mm)		
Weight	< 0.7 oz (< 20 g)	< 0.7 oz (< 20 g)		
Antenna Connector	U.FL Connector or pcb antenna	U.FL Connector or pcb antenna		
Certification	TT2530	TT2530		

CE

# (1) Description

CC2530 is a true system-on-chip(SoC) solution for IEEE 802.15.4, ZigBee and RF4CE applications. It can be very low total cost of materials to create a strong network of nodes. The CC2530 combines the excellent performance of the leading RF transceiver, the industry-standard enhanced 8051 CPU, system programmable flash,8-KB RAM and many other powerful features.CC2530 have four different types of flash memory version: CC2530F32/64/128/256, Each having 32/64/128/256 KB flash. CC2530 has a different mode of operation, the system makes it especially adapted to the requirements of the ultra-low power. The conversion between the run mode in a short time,to further ensure low energy consumption.CC2530F256 combined with the gold unit of Texas Instruments, the industry-leading ZigBee protocol stack (Z-Stack ™), provides a powerful and complete ZigBee solution. CC2530F64 combinaed of Texas Instruments the gold unit RemoTI, better to provide a powerful and complete ZigBee RF4CE remote control solutions.

GB2530 is the wireless module which using CC2530 and CC2591, has a small, peripheral simple, easy to use and excellent RF performance, leads to all external ports, and the convenience of the user, eliminating the need for debugging RF as well as other aspects of the complicated work more convenient embedded into the system and shorten the development cyclefaster to seize market opportunities and cost advantages.

# (2) Limiting values


		Least	Maximum	Unit
Voltage	All power supply pins must have	-0.3		V
	the same voltage	3.9		
Either a digital	-0.3	VDD	V	
		+0.3		
			$\leq$	
		3.9		
Input RF level			10	dBm
Storage		-40		° C
Temperature		125		
Range				
ESD (2)	All the liner are based on human		2	kV
	model JEDECSTD22			
	methodA114			
	According to the charged device		500	V
	model JEDECSTD22 method			
	C101			

<sup>(1)</sup> Beyond the limits of the parameters listed range may cause permanent damage to the device. These are just the limit parameter

- (2) Other conditions beyond the recommended operating conditions here under the functional operation is not implied. Super time
- (3) Conditions may affect the reliability of the equipment.

Warning: ESD sensitive devices. Handling such equipment must use precautions to prevent permanent damage.

## Low Power Pin description



	TT2530-L										
Pin	1	2	3	4	5	6	7	8	9	10	11
Function	P1. 4	P1_3	P1_2	P1_1	P1_0	P0_7	P0_6	P0_5	P0_4	P0_3	P0_2
Pin	12	13	14	15	16	17	18	19	20	21	22
Function	P0_1	P0_0	RES_N	GND	VCC	P2_2	P2_1	P2_0	P1_7	P1_6	P1_5
					TT2	530-H					
Pin	1	2	3	4	5	6	7	8	9	10	11
Function	P1_4	P1_3	P1_2	P1_1	P1_0	P0_7	P0_6	P0_5	P0_4	P0_3	P0_2
	EN	.		PA_EN		HGM		_			
Pin	12	13	14	15	16	17	18	19	20	21	22
Function	P0_1	P0_0	RES_N	GND	VCC	P2_2	P2_1	P2_0	P1_7	P1_6	P1_5

# Note: The PA\_EN, EN, HGM in the above table are representing CC2591's pins.

## Pin's Definition

ModulePin	Pin Description
1	P1_4 General-purpose I/O, Timer function, have 4-mA output drive strength
2	P1_3 General-purpose I/O, Timer function, interrupt function, have 4-mA output drive strength
3	P1-2 General-purpose I/O, interrupt function, have 4-mA output drive strength
4	P1-1 General-purpose I/O, Timer function, interrupt function, have 20-mA output drive strength
5	P1_0 General-purpose I/O, Timer function, interrupt function, have 20-mA output drive strength
6	P0-7 General-purpose I/O, ADC function, have 4-mA output drive strength
7	P0_6 General-purpose I/O, Timer function, ADC function, have 4-mA output drive strength
8	P0_5 General-purpose I/O, ADC function, Time functionr, UART $0  (RT)$ , UART $1  (RX)$ , SPI0 (C), SPI1 (MI), have 4-mA output drive strength
9	P0_4 General-purpose I/O, ADC function, Timer function, UART 0 (CT), SPI 0 (SS), SPI 1 (MO), UART 1 TX function, have 4-mA output drive strength

10	P0_3	$\label{eq:General-purpose I/O, ADC function, UART 0 (TX), UART 1 (RT), SPI0 (M0), SPI1} \\$
		(C), Timer function, have 4-mA output drive strength
11	P0_2	General-purpose I/O, ADC function, UART $0 (RX)$ , UART $1 (CT)$ , SPI $0 (MI)$ ,
		SPI1 (SS), Timer function, have 4-mA output drive strength
12	P0_1	General-purpose I/O, ADC function, have 4-mA output drive strength
13	P0_0	General-purpose I/O, ADC function, have 4-mA output drive strength
14	RES_N	Reset, active-low
15	GND	Ground
16	VCC	Working voltage for the IC to provide 2.0 - 3.6V
17	P2_2	DEBUG function pin (DC)
18	P2_1	DEBUG function pin (DD)
19	P2_0	General-purpose I/O, Timer function, have 4-mA output drive strength
20	P1_7	General-purpose I/O, have 4-mA output drive strength
21	P1_6	General-purpose I/O, have 4-mA output drive strength

22
----

## CC2591 and CC2530 's connection control logic

Pin's condition			Mada of quantian	
PA_EN	EN	HGM	Mode of operation	
0	0	x	CC2591 Power Down	
0	1	0	CC2591 RX Low Gain Mode (LGM)	
0	1	1	CC2591 RX <b>High Gain Mode</b> (HGM)	
1	0	х	CC2591 <b>TX</b>	
1	1	x	Not allowed	

TT2530-H Zigbee module , CC2591 and CC2530 connection,as follow picture:

